

COMP278 MIDTERM REVIEW

NAME _____

Complete this exam within 50 minutes. Write legibly and check your work. Good luck!

1. BINARY ARITHMETIC (20%)

Perform the following basic arithmetic operations.

(1) $(10111101)_2 + (10101101)_2$.

(2) $(10000111)_2 - (1011011)_2$.

2. NUMBER REPRESENTATION (20%)

Convert the following numbers to the specified bases:

(1) $(1400217236)_8$ in binary.

(2) The number above, $(1400217236)_8$, in hexadecimal.

(3) $(278)_{10}$ in binary.

(4) The number above, $(278)_{10}$, in octal.

3. COMBINATIONAL CIRCUIT DESIGN (60%)

Given two 2-bit binary numbers A & B , design a circuit that outputs F , the remainder of $(\frac{A}{B})$. If a division by zero has occurred, let $F = 3$.

- (1) To the left, draw the truth table for this circuit.
Label inputs as: A_1, A_0, B_1, B_0 . Label the output as F_1, F_0 .
- (2) To the right, write the Boolean algebraic expressions separately for F_1 and F_0 , then simplify them.

- (3) Draw the logic diagram for this circuit based on the simplified Boolean algebraic expressions. Label inputs and outputs as in the truth table.

- (4) Use DeMorgan's Law to derive $\overline{F_0}$.